

2WAY-0° POWER SPLITTER/COMBINERS

Designer's Kit K2-SBTC+



MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
THE SOLUTION!

5 to 2500MHz

SBTC-L+ Features

- Wideband, 50Ω
- Excellent amplitude unbalance
- Low insertion loss
- Low cost
- Leaded, open style package
- Micro-miniature size .166" x .150" x .155"
- Temperature stable LTCC base
- Low Temperature Co-fired Ceramic



All models are RoHS compliant

\$51.95
only **\$1** ea. kit (3 models, 5 of each, 15 total)

Kit K2-SBTC+ Electrical specifications of each model

Model	Freq. Range (MHz) f_L - f_U	Isolation (dB)			Insertion Loss (dB) Above 3.0dB				Phase Unbalance (Degrees)			Amplitude Unbalance (dB)			Power Input (W) (as a splitter) Max.					
		L*	M	U*	L*	M	U*	L*	M	U*	L*	M	U*							
		Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Max.				
SBTC-2-10L+	5-1000	29	20	25	18	21	16	0.3	0.7	0.3	0.8	0.5	1.4	3	3	5	0.6	0.5	0.5	0.5
SBTC-2-20L+	200-2000	—	—	20	14	—	—	—	—	0.8	2.2	—	—	—	10	—	—	0.8	—	0.5
SBTC-2-25L+	1000-2500	—	—	20	14	—	—	—	—	1.4	2.5	—	—	—	14	—	—	1.2	—	1.0

L = low range [f_L to $10f_L$] M = mid range [$10f_L$ to $f_U/2$] U = upper range [$f_U/2$ to f_U]

Protected under U.S. Patent 6,963,255

* When only specification for M range given, specification applies to entire frequency range.



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For quick access to product information see MINI-CIRCUITS CATALOG & WEB SITE

RF/IF MICROWAVE COMPONENTS

REV. OR
M104903
K2-SBTC+